

Inverter Module

Type WR-5073

ePower



Important Advantages

- Switch mode inverter
- High efficiency
- Excellent dynamic regulation
- High short-circuit current
- Short circuit proof
- Compact design
- Low weight
- Deep discharge protection for battery
- Electronic bypass
- N resp. N+1 operation (optional)
- Battery filter



GUSTAV KLEIN
POWER SUPPLIES - since 1948

Technical Data Type WR-5073

Nominal power	VA	1000	1500	2500	3000
	24 V-		X		
	48 V-			X	
	60 V-	X		X	X
	110 V-	X		X	X
	220 V-	X		X	X
Input voltage tolerance	V		-15 +20% (\leq 48V -10 +20%)		
AC output voltage	V			230 \pm 1%	
Output frequency	Hz		25 / 83,3 / 100 / 50 \pm 0,1 %		
Distortion factor	%			\leq 3 (at linear load)	
Power factor			Independent, rated power is reduced, if power factor deviates from 0.8 lagging		
Efficiency	%			81 ... 91	
Overload behavior			125% for 10 min., 110% for 20 min.		
Short circuit behavior			Short circuit proof, $I_K = 3x I_N$ for 20 msec., afterwards 2x I_N for 5 sec.		
Audibel noise	dB(A)			\leq 55	
EMC			EN 61000-6-2, EN 61000-6-4		
Test voltages					
Input - output	kV AC		3,75		
Input, output – ground	kV AC		2		
Cooling			„AF“ forced convection / „AN“ natural convection According to design		
Permissible altitude			1000 m above sea level		
Permissible climate			Indoor, 3K3 according to EN 60721-3-3		
Ambient temperature	°C		-5 ... +40		
Dimensions	mm		According data sheet		
Protection class			IP20, according to EN 60529		

Design

19"-housing or partial for mounting

In-/Output on terminals

Front connection

On-off switch for inverter

Operation mode selection switch:

- Continuous operation
- Standby operation
- Start-up operation

Functions

The inverter operates with most modern power transistors in PWM technique.

DC in- and AC output are electrically isolated.

An uninterrupted electronic bypass is included.

Protection and monitoring facilities:

Overload- and short circuit protection

Undervoltage at the input

Over- / and undervoltage at the output

Indications (LEDs in front panel):

- Load voltage o.k.
- DC voltage o.k.
- Load on inverter
- Load on AC mains
- Inverter fault
- Phase o.k.
- Operation

Remote alarm (2 floating contacts):

- Inverter fault
- Inverter operation

Options

External remote signals

Special frequencies

11/2012

subject to change without notice

D-86956 Schongau, Im Forchet 3
D-86952 Schongau, Postfach 1248
Tel. (08861) 209-0, Fax (08861) 209-180



A-6401 Inzing/Tirol, Schießstand 2
Tel. (05238) 54209-0
Fax (05238) 54209-23

E-Mail: vertrieb@gustav-klein.com Internet: www.gustav-klein.com